

# RT667

0.5W PMR446 16 Channels  
Two Way Radio

RETEVIS

## Feature:

- Scanning
- Busy Channel Lock
- TOT(Time-out Timer)
- Squelch
- VOX Function
- CTCSS&DCS Encode/Decode
- Battery Save Function
- Scrambler Function
- Flashlight
- Long Standby



# RT667

0.5W PMR446 16 Channels Two Way Radio

## General Specification:

Frequency Range:	PMR446
Power:	0.5W
Channel Capacity:	16
Battery capacity:	Li-ion 3000mAh
Working Voltage:	DC 3.7V
Working Temperature:	-10°C~50°C
Antenna Impedence:	50Ω
Weight (with battery):	106g
Size :	116*53*36mm

## Receiver:

Sensitivity:	≤0.2μV
Occupied Bandwidth:	≤16KHz
Selectivity:	≥65dB
Intermediation:	≥55dB
Audio Power output:	> 500mW
Modulation Distortion :	≤10%
Frequency Stability:	5ppm
Current:	55mA(when standby)150mA(when working)
Audio Response:	+7~-12.5dB

## Transmitter:

Modulation type:	FM
Spurious Radiation:	≤0.75μW
Modulation Noise:	<-40dB
Modulation Distortion :	≤5%
Frequency Stability:	5ppm
Maximum Deviation:	≤±5KHz
Current:	≤1200mA
Audio Response(300-3000Hz):	+6.5~-14dB
Adjacent Ch.power:	≥65dB
Intermediation sensitivity:	8-12mv

## Package includes:

- 1 x Radio
- 1 x Battery
- 1 x USB Charging Cable
- 1 x Belt Clip
- 1 x Sling
- 1 x User manual



## Shenzhen Retevis Technology Co.,Ltd

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli  
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: [www.retevis.com](http://www.retevis.com)

E-mail: [kam@retevis.com](mailto:kam@retevis.com)

Facebook: [facebook.com/retevis](https://facebook.com/retevis)



MADE IN CHINA