

RB35&RB635

FRS 16 Channels & PMR446 16 Channels

RETCVIS

Feature:

- Scanning
- Busy Channel Lock
- TOT(Time-out Timer)
- Squelch
- VOX Function
- CTCSS&DCS Encode/Decode
- Battery Save Function
- Scrambler Function
- Monitor
- Low battery voltage warning



RB35&RB635

FRS 16 Channels & PMR446 16 Channels

Specification:

Frequency Range:	US: FRS	EU: PMR446
Power:	US: 2W	EU: 0.5W
Channel Capacity:	16	
Battery capacity:	Li-ion 1200mAh	
Working Voltage:	DC 3.7V	
Working Temperature:	-10°C~50°C	
Antenna Impedence:	50Ω	
Weight (with battery):	125g	
Size:	153*55*25mm	

Receiver

Sensitivity:	≤0.16μV
Occupied Bandwidth:	≤16KHz
Selectivity:	≥65dB
Intermediation:	≥55dB
Audio Power output:	> 380mW
Modulation Distortion:	≤10%
Frequency Stability:	5ppm
Current:	55mA(when standby)150mA(when working)
Audio Response:	+7~-12.5dB

Transmitter

Modulation type:	FM
Spurious Radiation:	≤0.75μW
Modulation Noise:	<-40dB
Modulation Distortion:	≤5%
Frequency Stability:	5ppm
Maximum Deviation:	≤±5KHz
Current:	≤1000mA
Audio Response:	+6.5~-14dB
Adjacent Ch.power:	≥65dB
Intermediation sensitivity:	8-12mv

Package includes:

- 2 x Radio
- 2 x Battery
- 2 x Belt Clip
- 2x Sling
- 1 x User manual
- 1 x One for two charging lines



CE FC RoHS 

Shenzhen Retevis Technology Co.,Ltd

Add: 7/F, 13-C, Zhonghaixin Science&Technology Park, No.12 Ganli
6th Road, Jihua Street, Longgang District, Shenzhen, China

Web: www.retevis.com

E-mail: kam@retevis.com

Facebook: facebook.com/retevis



MADE IN CHINA